



# X500

## GSM/SMS Alarm System with Touch Keypad



## Rest Assured

Visible and intuitive operations that put you and your loved ones at absolute ease anywhere, anytime



**smanos®**  
Dream Big. Live Smart.

# X500

## GSM/SMS Alarm System with Touch Keypad

### Remote Wonders

After a regular working SIM card is inserted into the X500, the system becomes remote controllable by either simple SMS text messages or smartphone app commands. The app is available on both App Store and Google Play for free.

### Tap & Go

The system can be quickly disarmed by a simple tap of any authorized RFID tag. Every RFID tag and detection zone can be renamed for easy identification and notification of whom and where in the event of a triggered alarm.

### Phone in Disguise

The X500 can be used as a regular house phone or for remote listening in, and stores up to 5 smartphone and text message numbers.

### System Specifications

Power Input **DC 12V 500mA**

GSM Frequency **850/900/1800/1900 MHz**

Static Current **≤ 100mA**

Alarm Current **≤ 220mA**

Backup Battery **3.7V 1200mAh 18650 lithium battery**

Internal Siren Volume **95dB**

Supported Accessories **10 remote controls,  
50 sensors, and 50 RFID tags**

Radio Frequency **868 MHz**

Housing Material **ABS plastic**

Temperature **-10°C ~ +55°C**

Relative humidity **≤ 80% (non-condensing)**

Control Panel Dimensions (L×W×H) **220 x 130 x 26mm**

Bracket Dimensions (L×W×H) **100 x 22.5 x 8.15mm**

### Package Details

X500 Control Panel **x1**

MD2300 Wireless PIR Motion Detector **x1**

DS2300 Wireless Door/Window Contact **x2**

RE2300 Remote Control **x2**

PR2600 RFID Tag **x2**



[www.smanos.com](http://www.smanos.com)