

smanos®

Dream Big. Live Smart.



Smoke Alarm

Model No: SMK-500

Product Description

This photoelectric detector is designed to give early warnings of a developing fire by sounding its built-in siren. It is recommended for corridors, basements, penthouses or other confined spaces.

Features:

- *Battery-powered smoke alarm with test button
- *Blinking power light and 85dB built-in siren
- *Compatible with smanos alarm systems
- *Wireless range up to 80 meters (open area)
- *1 year battery life
- *Low battery LED indication

smanos®

Dream Big. Live Smart.



Specifications:

Power Supply:	DC 9V 6F22 battery x 1
Standby Current:	< 5uA
Alarm Current:	< 15mA
LED Frequency in Working State:	Once every 32 sec.
LED Frequency in Alarming State:	Once every 0.62 sec
Low Battery State:	Beep once with a LED flash per 60s (last for 30 days)
Alarm Decibel:	85dB/3m
Monitoring Area:	20 m ²
Radio Frequency:	868 MHz / 915MHz
Housing Material:	ABS plastic
Operating Condition:	Temperature -10°C ~ +55°C Relative Humidity < 80% (Non-condensing)
Size (L x W x H):	102 x 102 x 31 mm
Configuration:	SMK500 x1, bracket x 1