



X300

GSM/SMS Alarm System



Power in Disguise

Bringing reliable intrusion detection to a whole new level with industry-leading wireless technology and human-centric design ingenuity



smanos®
Dream Big. Live Smart.

X300

GSM/SMS Alarm System

Sentinel in Disguise

All the connection jacks are ingeniously tucked away and tamper-proofed. The patented IR tamper protection can be switched on or off; when activated, an alert will be sent out if the system controller is lifted by more than 3 cm/1.5 inches.

Relentlessly Reliable

Up to 5 phone numbers can be preprogrammed into the X300, and you can customize your own alarm message. The No. 1 phone number should be your own smartphone, or better yet, the number of your community security center, so that they can stop the burglar as soon as the alarm goes off.

Remote Wonders

The X300 can work with up to 50 wireless PIR motion detectors and 10 remote controls, which can be added or deleted at will in case you or your loved ones lose them.

Crystal Clear

Remote listening in and two-way voice communication are feasible and of Hi-Fi quality.

System Specifications

Model No. **X300**
Power Input **DC 12V 500mA**
GSM Frequency **850/900/1800/1900 MHz**
Static Current **≤ 65mA**
Alarm Current **≤ 230mA**
Backup Battery **3.7V 1200mAh 18650 lithium battery**
Internal Siren Volume **105dB**
Supported Accessories **10 remote controls, 50 sensors**
Radio Frequency **868 MHz**
Housing Material **PC plastic**
Temperature **-10°C ~ +55°C**
Relative humidity **≤ 80% (non-condensing)**
Control Panel Dimensions (L×W×H) **175 x 39 x 97 mm**
Bracket Dimensions (L×W×H) **135.5 x 61 x 20 mm**

Package Details

X300 Control Panel ×1
MD2300 Wireless PIR Motion Detector ×1
DS2300 Wireless Door/Window Contact ×1
RE2300 Remote Control ×2



www.smanos.com